

SV-QSFP-40G-PLR4

40GBase aggregating 4 x 1310nm duplex SM (MPO-12) with DDM, distance up to 10km, supporting 40GE, Infiniband QDR, DDR and SDR



Features

- 4 Parallel lanes design
- Up to 11.2Gb/s data rate per channel
- Aggregate Bandwidth of up to 44.0G
- QSFP+ MSA compliant
- Up to 10km transmission on single mode fiber (SMF)
- Maximum power consumption 3.5W
- Single +3.3V power supply
- Operating case temperature: 0~70°C
- RoHS-6 compliant

Applications

- 40G Ethernet
- Infiniband QDR, DDR and SDR
- Datacenter and Enterprise networking

| Part number | Description |
|-------------------------|--|
| SV-QSFP-40G-PLR4 | Starview QSFP+ 40Gbps module 40GBase aggregating 4 x 1310nm duplex SM (MPO-12) with Digital Diagnostic Monitoring (DDM), distance up to 10km, supporting 40GE, Infiniband QDR, DDR and SDR |

Absolute Maximum Ratings

| Parameter | Symbol | Min. | Max. | Unit |
|--------------------------------------|----------|------|------|------|
| Storage Temperature | T_s | -40 | 85 | °C |
| Operating Case Temperature | T_{OP} | 0 | 70 | °C |
| Power Supply Voltage | V_{CC} | -0.5 | 3.6 | V |
| Relative Humidity (non-condensation) | RH | 0 | 85 | % |
| Damage Threshold, each Lane | TH_d | 3.3 | | dBm |

Recommended Operating Conditions

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Note |
|----------------------------|--------|-------|---------|----------|------|------|
| Operating Case Temperature | TOP | 0 | | 70 | °C | |
| Power Supply Voltage | VCC | 3.135 | 3.3 | 3.465 | V | |
| Data Rate, each Lane | | | 10.3125 | 11.2 | Gb/s | |
| Control Input Voltage High | | 2 | | V_{CC} | V | |
| Control Input Voltage Low | | 0 | | 0.8 | V | |
| Link Distance G652 | D | 0.002 | | 10 | km | |

Optical Characteristics

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Note |
|---|---------------|------|------|------|-------|------|
| Transmitter | | | | | | |
| Center Wavelength | λ_C | 1260 | 1310 | 1355 | nm | |
| Side Mode Suppression Ratio | SMSR | 30 | | | dB | |
| Total Average Launch Power | PT | | | 7.5 | dBm | |
| Average Launch Power, each Lane | PAVG | -5.5 | | 1.5 | dBm | 1 |
| Optical Modulation Amplitude (OMA), each Lane | POMA | -4.5 | | 2.5 | dBm | 2 |
| Difference in Launch Power between any Two Lanes (OMA) | $P_{tx,diff}$ | | | 6.5 | dB | |
| Launch Power in OMA minus Transmitter and Dispersion Penalty (TDP), each Lane | | -5.5 | | | dBm | |
| TDP, each Lane | TDP | | | 3.2 | dB | |
| Extinction Ratio | ER | 3.5 | | | dB | |
| Relative Intensity Noise | RIN | | | -128 | dB/Hz | |
| Optical Return Loss Tolerance | TOL | | | 12 | dB | |
| Transmitter Reflectance | RT | | | -12 | dB | |

| | | | | | | |
|--|-------------|------------------------------------|------|-------|-----|--------------|
| Average Launch Power OFF Transmitter, each Lane | Poff | | -30 | | dBm | |
| Transmitter Eye Mask Definition {X1, X2, X3, Y1, Y2, Y3} | | {0.25, 0.4, 0.45, 0.25, 0.28, 0.4} | | | | |
| Receiver | | | | | | |
| Center Wavelength | λ_C | 1260 | 1310 | 1355 | nm | |
| Damage Threshold, each Lane | THd | 3.3 | | | dBm | 3 |
| Average Power at Receiver Input, each Lane | | -12.6 | | 1.5 | dBm | |
| Receiver Reflectance | RR | | | -12 | dB | |
| Receive Power (OMA), each Lane | | | | 2.5 | dBm | |
| Receiver Sensitivity in OMA, each Lane | SEN | | | -12.6 | dBm | Infor-mative |
| Difference in Receive Power between any Two Lanes (OMA) | Prx,diff | | | 7.5 | dB | |
| LOS Assert | LOSA | -30 | | | dBm | |
| LOS Deassert | LOSD | | | -15 | dBm | |
| LOS Hysteresis | LOSH | 0.5 | | | dB | |
| Receiver Electrical 3 dB upper Cutoff Frequency, each Lane | Fc | | | 12.3 | GHz | |

Note(1): The maximum transmitter average optical power of 1.5 dBm is well within the guardband of receiver overload specifications of commercially available 10GBASE-LR SFP+ transceivers offered by Starview and other vendors.

Note(2): Even if the TDP < 1 dB, the OMA min must exceed the minimum value specified here.

Note(3): The receiver shall be able to tolerate, without damage, continuous exposure to a modulated optical input signal having this power level on one lane. The receiver does not have to operate correctly at this input power.

Digital Diagnostics Functions

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Note |
|---|--------------|------|------|------|------|----------------------|
| Temperature monitor absolute error | DML_Temp | -3 | | 3 | °C | Over operating temp |
| Supply voltage monitor absolute error | DML_VCC | -0.1 | | 0.1 | V | Full operating range |
| Channel RX power monitor absolute error | DML_RX_Ch | -2 | | 2 | dB | 1 |
| Channel Bias current monitor | DML_Ibias_Ch | -10% | | 10% | mA | |
| Channel TX power monitor absolute error | DML_TX_Ch | -2 | | 2 | dB | 1 |

Note(1): Due to measurement accuracy of different single mode fibers, there could be an additional +/-1 dB fluctuation, or a +/- 3 dB total accuracy

Electrical Characteristics

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Note |
|--|---------------------|----------------------------|-----------------------|------|------------------|-----------------------------------|
| Power Consumption | | | | 3.5 | W | |
| Supply Current | I _{cc} | | | 1.1 | A | |
| Transceiver Power-on Initialization Time | | | | 2000 | ms | 1 |
| Transmitter(each lane) | | | | | | |
| Single-ended Input Voltage Tolerance (Note 2) | | -0.3 | | 4.0 | V | Referred to TP1 signal common |
| AC Common Mode Input Voltage Tolerance (RMS) | | 15 | | | mV | |
| Differential Input Voltage Swing Threshold | | 50 | | | mV _{pp} | LOSA Threshold |
| Differential Input Voltage Swing | V _{in,pp} | 190 | | 700 | mV _{pp} | |
| Differential Input Impedance | Z _{in} | 90 | 100 | 110 | Ohm | |
| Differential Input Return Loss | | See IEEE 802.3ba 86A.4.11 | | | dB | 10MHz-11.1GHz |
| J2 Jitter Tolerance | Jt2 | 0.17 | | | UI | |
| J9 Jitter Tolerance | Jt9 | 0.29 | | | UI | |
| Data Dependent Pulse Width Shrinkage (DDPWS) Tolerance | | 0.07 | | | UI | |
| Eye Mask Coordinates {X1, X2 Y1, Y2} | | | 0.11, 0.31 95, 350 | | UI mV | Hit Ratio = 5x10 ⁻⁵ |
| Receiver(each lane) | | | | | | |
| Single-ended Output Voltage | | -0.3 | | 4.0 | V | Referred to signal common |
| AC Common Mode Output Voltage (RMS) | | | | 7.5 | mV | |
| Differential Output Voltage Swing | V _{out,pp} | 300 | | 850 | mV _{pp} | |
| Differential Output Impedance | Z _{out} | 90 | 100 | 110 | Ohm | |
| Termination Mismatch at 1MHz | | | | 5 | % | |
| Differential Output Return Loss | | See IEEE 802.3ba 86A.4.2.1 | | | dB | 10MHz-11.1GHz |
| Common Mode Output Return Loss | | See IEEE 802.3ba 86A.4.2.2 | | | dB | 10MHz-11.1GHz |
| Output Transition Time | | 28 | | | ps | 20% to 80% |
| J2 Jitter Output | Jo2 | | | 0.42 | UI | |
| J9 Jitter Output | Jo9 | | | 0.65 | UI | |
| Eye Mask Coordinates {X1, X2 Y1, Y2} | | | 0.29, 0.5 150, 425 | | UI mV | Hit Ratio = 5x10 ⁻⁵ |

Note(1): Power-on Initialization Time is the time from when the power supply voltages reach and remain above the minimum recommended operating supply voltages to the time when the module is fully functional.

Note(2): The single ended input voltage tolerance is the allowable range of the instantaneous input signals