

SV-QSFP-40G-PSR4

40G Base aggregating 4 x 850nm duplex MM (MPO-12), distance up to 100m on 50/125um OM3 MM fiber, 150m for 50/125um MM OM4 MM fiber



Features

- 4 independent full-duplex channels
- Up to 11.2Gb/s data rate per channel
- MTP/MPO optical connector
- QSFP+ MSA compliant
- Digital diagnostic capabilities
- Up to 100m transmission on OM3 multi-mode ribbon fiber
- CML compatible electrical I/O
- Single +3.3V power supply
- Operating case temperature: 0~70°C
- XLPP1 electric interface
- Maximum power consumption 1.5W
- RoHS-6 compliant

Applications

- Rack to Rack
- Data Center
- Infiniband QDR, DDR and SDR
- 40G Ethernet

Part number	Description
SV-QSFP-40G-PSR4	Starview QSFP+ 40Gbps module 40GBase aggregating 4 x 850nm duplex MM (MPO-12) with Digital Diagnostic Monitoring (DDM), distance up to 100m on 50/125um OM3 MM fiber, 150m for 50/125um MM OM4 MM fiber, supporting 40GE, Infiniband QDR, DDR and SDR

Absolute Maximum Ratings

Parameter	Symbol	Min.	Max.	Unit
Storage Temperature	T_s	-40	85	°C
Operating Case Temperature	T_{OP}	0	70	°C
Power Supply Voltage	V_{CC}	-0.5	3.6	V
Relative Humidity (non-condensation)	RH	0	85	%
Damage Threshold, each Lane	TH_d	3.4		dBm

Recommended Operating Conditions

Parameter	Symbol	Min.	Typ.	Max.	Unit	Note
Operating Case Temperature	T_{OP}	0		70	°C	
Power Supply Voltage	V_{CC}	3.135	3.3	3.465	V	
Data Rate, each Lane			10.3125	11.2	Gb/s	
Control Input Voltage High		2		V_{CC}	V	
Control Input Voltage Low		0		0.8	V	
Link Distance with G652	D			100	m	

Optical Characteristics

Parameter	Symbol	Min.	Typ.	Max.	Unit	Note
Center Wavelength	λ_c	840	850	860	nm	
RMS Spectral Width	$\Delta\lambda_{rms}$		0.5	0.65	nm	
Average Optical Power, each Lane	P_{AVG}	-7.6		1.0	dBm	1
Optical Modulation Amplitude (OMA), each Lane	P_{OMA}	-5.6		3.0	dBm	2
Difference in Launch Power between any Two Lanes (OMA)	$P_{tx,diff}$			4.0	dB	
Peak Power, each Lane	PP_T			4.0	dBm	
Launch Power in OMA minus Transmitter and Dispersion Penalty (TDP), each Lane	OMA-TDP	-6.5			dBm	
TDP, each Lane				3.5	dB	
Extinction Ratio	ER	3.0			dB	
Relative Intensity Noise	RIN			-128	dB/Hz	12dB reflection
Optical Return Loss Tolerance	TOL			12	dB	
Average Launch Power OFF Transmitter, each Lane	P_{off}			-30	dBm	
Encircled Flux		$\geq 86\%$ at 19 μ m				
		$\leq 30\%$ at 4.5 μ m				

Transmitter Eye Mask
 Definition {X1, X2, X3, Y1, Y2, Y3} 0.23, 0.34, 0.43, 0.27, 0.35, 0.4

		Receiver				
Center Wavelength	λ_c	840	850	860	nm	
Damage Threshold, each Lane	TH_d	3.4			dBm	3
Average Power at Receiver Input, each Lane		-9.5		2.4	dBm	
Receiver Reflectance	R_R			-12	dB	
Receive Power (OMA), each Lane				3.0	dBm	
Receiver Sensitivity (OMA), each Lane	SEN			-8.4	dBm	
Stressed Receiver Sensitivity (OMA), each Lane				-5.4	dBm	4
Peak Power, each Lane	PP_R			4.0	dBm	
LOS Assert	LOSA	-30			dBm	
LOS Deassert	LOSD			-12	dBm	
LOS Hysteresis	LOSH	0.5			dB	
Conditions of Stress Reliever Sensitivity Test Note(5)						
Vertical Eye Closure Penalty, each Lane			1.9		dB	
Stressed Eye J2 Jitter, each Lane			0.3		UI	
Stressed Eye J9 Jitter, each Lane			0.47		UI	
OMA of each aggressor lane			-0.4		dBm	

Note(1): The maximum transmitter average optical power of 1.0 dBm is well within the guardband of receiver overload specifications of commercially available 10GBASE-SR SFP+ transceivers offered by Starview and other vendors.

Note(2): Even if the TDP < 0.9 dB, the OMA min must exceed the minimum value specified here.

Note(3): The receiver shall be able to tolerate, without damage, continuous exposure to a modulated optical input signal having this power level on one lane. The receiver does not have to operate correctly at this input power.

Note(4): Measured with conformance test signal at receiver input for BER = 1x10⁻¹².

Note(5): Vertical eye closure penalty and stressed eye jitter are test conditions for measuring stressed receiver sensitivity. They are not characteristics of the receiver.

Digital Diagnostics Functions

Parameter	Symbol	Min.	Typ.	Max.	Unit	Note
Temperature monitor absolute error	DMI_Temp	-3		3	degC	Over operating temp
Supply voltage monitor absolute error	DMI_VCC	-0.15		0.15	V	Full operating range
Channel RX power monitor absolute error	DMI_RX_Ch	-2		2	dB	1
Channel Bias current monitor	DMI_Ibias_Ch	-10%		10%	mA	Ch1~Ch4

Channel TX power monitor absolute error	DML_TX_Ch	-2	2	dB	1
---	-----------	----	---	----	---

Note(1): Due to measurement accuracy of different single mode fibers, there could be an additional +/-1 dB fluctuation, or a +/- 3 dB total accuracy

Electrical Characteristics

Parameter	Symbol	Min.	Typ.	Max.	Unit	Note
Power Consumption				1.5	W	
Supply Current	Icc			450	A	
Transceiver Power-on Initialization Time				2000	ms	1
Transmitter(each lane)						
Single-ended Input Voltage Tolerance (Note 2)		-0.3		4.0	V	Referred to TP1 signal common
AC Common Mode Input Voltage Tolerance (RMS)		15			mV	
Differential Input Voltage Swing Threshold		50			mVpp	LOSA Threshold
Differential Input Voltage Swing	Vin,pp	180		1200	mVpp	
Differential Input Impedance	Zin	90	100	110	Ω	
Differential Input Return Loss		See IEEE 802.3ba 86A.4.11			dB	10MHz-11.1GHz
J2 Jitter Tolerance	Jt2	0.17			UI	
J9 Jitter Tolerance	Jt9	0.29			UI	
Data Dependent Pulse Width Shrinkage (DDPWS) Tolerance		0.07			UI	
Eye Mask Coordinates {X1, X2 Y1, Y2}			0.11, 0.31 95, 350		UI mV	Hit Ratio= 5x10 ⁻⁵
Receiver(each lane)						
Single-ended Output Voltage		-0.3		4.0	V	Referred to signal common
AC Common Mode Output Voltage (RMS)				7.5	mV	
Differential Output Voltage Swing	Vout,pp	600		800	mVpp	
Differential Output Impedance	Zout	90	100	110	ohm	
Termination Mismatch at 1MHz				5	%	
Differential Output Return Loss		See IEEE 802.3ba 86A.4.2.1			dB	10MHz-11.1GHz
Common Mode Output Return Loss		See IEEE 802.3ba 86A.4.2.2			dB	10MHz-11.1GHz
Output Transition Time		28			ps	20% to 80%
J2 Jitter Output	Jo2			0.42	UI	
J9 Jitter Output	Jo9			0.65	UI	
Eye Mask Coordinates {X1, X2 Y1, Y2}			0.29, 0.5 150, 425		UI mV	Hit Ratio = 5x10 ⁻⁵

Note(1): Power-on Initialization Time is the time from when the power supply voltages reach and

remain above the minimum recommended operating supply voltages to the time when the module is fully functional.

Note(2): The single ended input voltage tolerance is the allowable range of the instantaneous input signals